

fabricant	P/N	repere	Freq max	GAIN	Pout (dBm)	max in (dBm)	nf	I (ma)	P max	I max	Volts
Avantek/HP	MSA0385	A03	2500	12	10	13	6.0	35	400	70	5
MINICIRCUITS	MAR1	marron	1000	17.5	1.5	10	5.0	40	100	17	5
Avantek/HP	MSA0304	3	1600	11	10	13	6.0	70	400	35	5
Avantek/HP	MSA0785	A07	2000	12.5	5.5	13	5.0	60	275	22	4
Avantek/HP	MSA0485	A04	3600	8	12.5	13	7.0	50	500	85	5.25
Avantek/HP	MSA0986	A09	3000	7.2	10.5	13	6.2	65	500	35	6.2
MINICIRCUITS	MAR3	orange	2000	12	10	15	6.0	70	400	35	5
Avantek/HP	MSA0285	A02	2600	12	4.5	13	6.5	25	325	60	5
Avantek/HP	MSA0185	A01	1000	17	1.5	13	5.5	17	200	40	5
MINICIRCUITS	MAR2	rouge	2000	11	4.5	13	6.5	60	325	25	5
MINICIRCUITS	MAR4	jaune	1000	8.2	12.5	15	7.0	85	500	50	5
Avantek/HP	MSA0486	A04	3200	8	12.5	13	7.0	85	500	50	5.25

[Une feuille a imprimer et a avoir sous la main => http://F1CHF.FREE.FR/fichiers/utilisation-MMIC.pdf](http://F1CHF.FREE.FR/fichiers/utilisation-MMIC.pdf)